



MPS 3000

Motor Protection and Control Relay

The MPS-3000 is an ideal solution for Medium and Low Voltage motors because it provides a comprehensive control and protection package. The MPS-3000 monitors 3-phase currents and voltage using 10 RTD/ Thermistor temperature inputs.

The MPS-3000 is available in two configurations - as a protection relay and as a motor controller. The unit can also be mounted vertically or horizontally based upon the system configuration.

Certified Protection

ANSI/IEEE C37.2	PROTECTIONS	MPS 3000
3	Communication failure / Internal failure	✓
27	Under-voltage	✓
32L	Under Power Level 1/2	✓
37	Under current Level 1/2	✓
46	Current Imbalance Level 1/2	✓
47	Phase sequence/loss	✓
48	Max. Start Time	✓
49R	High Temp. Level 1/2, sensors 1-10	✓
49/51	Thermal Capacity Level 1/2	✓
50	Over Current Level 2 - Short	✓
50G	Ground Fault Level during starting	✓
50G/N	Ground Fault Level 1/2	✓
51L	Load Increase - Alarm	✓
51R	Over Current Level 1 - Jam	✓
55	Lead / Lag PF / Low Power Factor	✓
59	Over-voltage Level 1/2	✓
66	Too Many Starts Level 1	✓
49R	RTD 1-10 Level 1/3	✓
74	Control Circuit Open	✓
74	Welded Contactor	✓
86 or 94	External Fault 1/2/3	✓

Advanced Features

- Monitoring 10 temperature inputs, 3-phase current, voltage and energy
- Power measurement (3-phase voltage measurement)
- Statistical data of last 10 trips with time and date stamp
- RTD bias for thermal overload
- Multiple Thermal Overload curves
- Too Many Starts pre-alarm, configurable to energize dedicated output relay
- Capture and display of min and max RMS, average of 3-phase current, one voltage, min and max frequency
- Ground Fault setting during start eliminates nuisance trips
- MODBUS communication, remote parameter programming, control and supervision.
- Programmable discrete inputs/output
- 4 programmable analog outputs
- 4 programmable analog inputs

For more information, please contact:

Rick Ligeikis

Phone: +1 304 523 4700
 Cell: +1 864 314 9046
 Fax: +1 304 523 4039
 Home Fax: +1 864 225 5512
rlikeikis@samincoinc.com

Ed McFall

Phone: +1 304 523 4700
 Cell: +1 304 638 7994
emcfall@samincoinc.com

Kenny Boles

Phone: +1 239 561 1561
 Cell: +1 304 634 3380
kboles@samincoinc.com



MPS 3000-C

Motor Protection Controller

The MPS-3000-C includes the same functionality as the standard MPS-3000, but it incorporates motor control capabilities. It includes various starting methods including Direct Online, Star Delta, Soft Starters, Reversing and Two Speed. The MPS-3000-C includes twenty dry optically isolated logic inputs that are used to enable different types of control.



How To Order

Example:

MPS-3000

P

Relay Type

P - Motor Protection Relay
C - Motor Protection Controller

V

Construction

V - Vertical
H - Horizontal

1P

Thermal Sensor

1P - 10 RTD Platinum
1C - 10 RTD Copper
TP - 4 Thermistors+ 6 RTD (Pt100)
TC - 4 Thermistors+ 6 RTD (Copper)

2

Control Voltage

2 - 110-230VAC
2S - 110-230V AC/DC w/ separate AUX
3 - 19-60VDC

3P




Options

2- Trip on disconnected RTD
M- Modbus
P- Profibus

Model	Unit Dimensions (mm)			Weight (kg)
	H	W	D	
Vertical	310	134	140	3.1
Horizon	140	310	134	



Meeting your needs across industries



For More Information

www.solcon.com

contact@solcon.com

For more information, please contact:

Rick Ligeikis

Phone: +1 304 523 4700

Cell: +1 864 314 9046

Fax: +1 304 523 4039

Home Fax: +1 864 225 5512

rigeikis@samincoinc.com

Ed McFall

Phone: +1 304 523 4700

Cell: +1 304 638 7994

emcfall@samincoinc.com

Kenny Boles

Phone: +1 239 561 1561

Cell: +1 304 634 3380

kboles@samincoinc.com

